

Installation

S17475 - IP65 - 15W LED CCT Adjustable Emergency Polo Bulkhead

1

Switch OFF at mains supply before installing

2

Hold the base securely and twist to unlock and remove the diffuser

3

Loosen screws and twist to remove gear tray from the base, detach safety belt

4

Ensure product is located in the correct location and mark surface

5

Use correct drill bit to drill screw holes

6

Pull power supply through hole in the base plate

7

Install the fixing screws to the base plate

8

Attach safety belt to gear tray

9

Press the individual terminal and insert the correct incoming supply before releasing the terminal to secure. The product MUST be earthed

Note: Please ensure there are no switches, PIRs etc in the permanent live feed, as switching of the emergency pack will reduce the battery's life considerably

10

Change battery switch to 'ON' position

11

Push the "Test" button on the battery pack for at least 2 seconds. If LEDs are lit, the emergency function is working.

12

Align gear tray with screws and tighten

13

Use the CCT selection switch on the gear tray to select the desired colour temperature

14

Push and twist the diffuser back into place

15

Return power. Switch ON at mains supply

Packaging Information

	SIZE(CM)	N.W/pc (KGS)	G.W.(KGS)	Q'TY(PCS)
Carton	69*66*36.5	1.1	15.2	12

	CTNS	Q'TY(PCS)	VOLUME(CBM)
20" standard container	150	1800	28
40" standard container	320	3840	58

